

NC-SERIES

INDOOR / OUTDOOR SET-UP LOUDSPEAKER

NTS

TECHNICAL SPECIFICATION



+ Line Transformer + Power Amplifier

■ NC-402 / 402T

Rated power	25W RMS
Power [MAX]	50W
Bass speaker	4"
Speakers	1 tweeter
Connections	2-pole terminal
Max SPL	88dB
Impedance	8Ω
Frequency-range	70Hz ~ 18KHz
Dimension [HxWxD]	243x151x150 mm.
NC-402T Line Transformer	2/4/8/16 W (100V)

■ NC-502 / 502T / 502A

Rated power	35W RMS
Power [MAX]	75W
Bass speaker	5"
Speakers	1 tweeter
Connections	2-pole terminal
Max SPL	89dB
Impedance	8Ω
Frequency-range	60Hz ~ 18KHz
Dimension [HxWxD]	247x158x152 mm.
NC-502T Line Transformer	2/4/8/16 W (100V)
NC-502A Power output	25W RMS
Frequency-range	20Hz ~ 20KHz
Equalization	2 band EQ +/-15dB
Gain	30dB (max)

■ NC-602 / 602T / 602A

Rated power	50W RMS
Power [MAX]	100W
Bass speaker	6.5"
Speakers	1 tweeter
Connections	2-pole terminal
Max SPL	89dB
Impedance	8Ω
Frequency-range	55Hz ~ 20KHz
Dimension [HxWxD]	348x208x203 mm.
NC-602T Line Transformer	4/8/16/30 W (100V)
NC-602A Power output	50W RMS
Frequency-range	20Hz ~ 20KHz
Equalization	2 band EQ +/-15dB
Gain	30dB (max)

■ NC-802 / 802T

Rated power	85W RMS
Power [MAX]	125W
Bass speaker	8"
Speakers	1 tweeter
Connections	2-pole terminal
Max SPL	90dB
Impedance	8Ω
Frequency-range	45Hz ~ 20KHz
Dimension [HxWxD]	420x255x250 mm.
NC-802T Line Transformer	4/8/16/30 W (100V)

<http://www.nts-solution.com>

All features & specifications are subjected to change without notice.

NTS

บริษัท เอ็นทีเอส อิเล็กทรอนิกส์ โซลูชั่น จำกัด
NTS Electronic Solution Co., Ltd.

1439-1441 ถนนเจริญนคร แขวงบางลำภูล่าง เขตคลองสาน กรุงเทพฯ 10600

โทรศัพท์: 0-2438-7023-4, 0-2437-7639 โทรสาร: 0-2437-1897

<http://www.nts-solution.com> E-mail: nts@nts-solution.com

1439-1441 Charoenakorn Rd. Banglumpoolang Klongsan Bangkok 10600, Thailand

Tel: (+66-2) 438-7023-4, (+66-2) 437-7639 Fax: (+66-2) 437-1897