

RMV-SERIES

STEREO MIXER with 99 DSP EFFECT & USB INPUT



RMV6/2FX : 6 Channel Mixer (2 Mono / 2 Stereo)

RMV8/2FX : 8 Channel Mixer (4 Mono / 2 Stereo)

TECHNICAL SPECIFICATION

- Mono and stereo input with gold plated XLR and balanced line input
- 3 band EQ on mono input and 2 band EQ on stereo input
- Peak LED on all mono and stereo channel
- 1 Aux send per channel for external effects and monitoring
- Highly accurate 8 segment bargraph meter
- 99 DSP digital multi effect
- +48V phantom power supply
- MP3 input and playback

Input Channel

Mic Input Electronically balanced
 : Frequency Response 10Hz to 200KHz
 : Gain Range +14dB to +60dB
 : SNR 120dB E.I.N.
 Line Input Electronically balanced
 : Frequency Response 10Hz to 130KHz
 : Gain Range -6dB to +38dB
 : SNR 95dB E.I.N.

Stereo Channel

Frequency Response 10Hz to 70KHz
 Gain Range : Line -8dB to +15dB
 : Mic +13dB to +60dB
 SNR : Line 96dB
 : Mic 104dB E.I.N.

Equalization

Low 80Hz, +/-15dB
 Mid 2.5KHz, +/-15dB
 High 12KHz, +/-15dB

Main Mix

Main Output +28dBu balanced / +22dBu unbalanced
 AUX Send +22dBu unbalanced
 Tape Out +22dBu unbalanced
 Phone Output +15dBu

Physical Dimension and Weight

Dimension [HxWxD] 72 x 210 x 250 mm. [RMV6/2FX]
 72 x 260 x 250 mm. [RMV8/2FX]
 Weight 3.0 kg. [RMV6/2FX]
 3.7 kg. [RMV8/2FX]

<http://www.nts-solution.com>

All features & specifications are subjected to change without notice.



บริษัท เอ็นทีเอส อิเล็กทรอนิกส์ โซลูชั่น จำกัด
 NTS Electronic Solution Co., Ltd.

1439-1441 ถนนเจริญนคร แขวงบางลำภูล่าง เขตคลองสาน กรุงเทพฯ 10600

โทรศัพท์: 0-2438-7023-4, 0-2437-7639 โทรสาร: 0-2437-1897

<http://www.nts-solution.com> E-mail: nts@nts-solution.com

1439-1441 Charoenakorn Rd. Banglumpoolang Klongsan Bangkok 10600, Thailand

Tel: (+66-2) 438-7023-4, (+66-2) 437-7639 Fax: (+66-2) 437-1897