E1832FX

STEREO MIXER WITH 99 DSP EFFECT

E1832FX : 14 Channel Mixer (6 Mono / 4 Stereo) with 99 DSP Effect

TECHNICAL SPECIFICATION

- Insert point on mono input
- 3 band EQ with sweepable midrange on mono input
- 4 band EQ on stereo input
- 2 Aux send for external effects and monitoring
- Peak LED on all input
- LOW CUT switch on mono input
- MUTE and SOLO switch on all input
- Built in 99 program digital effect
- Voice canceller function
- 9 band graphic EQ
- Stereo output and 2 group output
- +48V phantom power supply

Frequency Response ..... < 10Hz - 150kHz, -1dB
..... < 10Hz - 200kHz, -3dB
T.H.D. ..... 0.005% / 0.004% A-weighted
Signal to Noise Ratio ..... 110dB / 112dB A-weighted
Mono Channel EQ : High ..... +/-15dB, 12KHz
: Mid ... +/-15dB, sweepable 100Hz to 8KHz
: Low ..... +/-15dB, 80Hz
Stereo Channel EQ : High ..... +/-15dB, 12KHz
: High - Mid ..... +/-15dB, 3KHz
: Low - Mid ..... +/-15dB, 500Hz
: Low ..... +/-15dB, 80Hz
Power Requirement ..... AC 100V to 240V, 50/60Hz

http://www.nts-solution.com

All features & specifications are subjected to change without notice.

บริษัท เอ็นทีเอส อิเล็กทรอนิกส์ โซลูชั่น จำกัด
NTS Electronic Solution Co., Ltd.

1439-1441 ถนนเจริญนคร แขวงบางลำภูล่าง เขตคลองสาน กรุงเทพฯ 10600
โทรศัพท์: 0-2438-7023-4, 0-2437-7639 โทรสาร: 0-2437-1897
http://www.nts-solution.com E-mail: nts@nts-solution.com
1439-1441 Charoennakorn Rd. Banglumpoolang Klongsan Bangkok 10600, Thailand
Tel: (+66-2) 438-7023-4, (+66-2) 437-7639 Fax: (+66-2) 437-1897