

# PMU-SERIES

POWER MIXER with DIGITAL EFFECT & USB INPUT



USB / SD CARD

MP3 INPUT



## PMU-SERIES

Stereo Power Mixer 6/8/12 Channel with Digital Effect & USB Input

### TECHNICAL SPECIFICATION

- USB / SD card for MP3 input
- Build in 16 DSP effector
- 3 band EQ on all channel input
- 1 Aux send per channel for external effect and monitoring
- 7 band EQ on stereo output
- Dual 10 band level display main output

- PMU-601 : 6 Mono Input + Digital Effect
- PMU-801 : 8 Mono Input + Digital Effect
- PMU-1201 : 12 Mono Input + Digital Effect

| POWER SECTION :             | PMU-601                          | PMU-801                          | PMU-1201                         |
|-----------------------------|----------------------------------|----------------------------------|----------------------------------|
| Input Channel .....         | 6 mono input .....               | 8 mono input .....               | 12 mono input .....              |
| Power Output .....          | 250W x 2 @ 4Ω .....              | 250W x 2 @ 4Ω .....              | 300W x 2 @ 4Ω .....              |
| .....                       | 150W x 2 @ 8Ω .....              | 150W x 2 @ 8Ω .....              | 180W x 2 @ 8Ω .....              |
| Frequency Response .....    | 18Hz - 18KHz .....               | 18Hz - 18KHz .....               | 18Hz - 18KHz .....               |
| T.H.D. ....                 | 0.005% / 0.004% A-weighted ..... | 0.005% / 0.004% A-weighted ..... | 0.005% / 0.004% A-weighted ..... |
| Signal to Noise Ratio ..... | 110dB / 112dB A-weighted .....   | 110dB / 112dB A-weighted .....   | 110dB / 112dB A-weighted .....   |
| Parametric EQ               |                                  |                                  |                                  |
| HIGH .....                  | +/-15dB, 12kHz .....             | +/-15dB, 12kHz .....             | +/-15dB, 12kHz .....             |
| MID .....                   | +/-15dB, 100Hz~6kHz .....        | +/-15dB, 100Hz~6kHz .....        | +/-15dB, 100Hz~6kHz .....        |
| LOW .....                   | +/-15dB, 80Hz .....              | +/-15dB, 80Hz .....              | +/-15dB, 80Hz .....              |
| Dimension [HxWxD] .....     | 130 x 420 x 400 mm. ....         | 130 x 553 x 400 mm. ....         | 130 x 686 x 400 mm. ....         |

<http://www.nts-solution.com>

All features & specifications are subjected to change without notice.



บริษัท เอ็นทีเอส อิเล็กทรอนิกส์ โซลูชั่น จำกัด  
NTS Electronic Solution Co., Ltd.

1439-1441 ถนนเจริญนคร แขวงบางลำภูล่าง เขตคลองสาน กรุงเทพฯ 10600

โทรศัพท์: 0-2438-7023-4, 0-2437-7639 โทรสาร: 0-2437-1897

<http://www.nts-solution.com> E-mail: [nts@nts-solution.com](mailto:nts@nts-solution.com)

1439-1441 Charoenakorn Rd. Banglumpoolang Klongsan Bangkok 10600, Thailand

Tel: (+66-2) 438-7023-4, (+66-2) 437-7639 Fax: (+66-2) 437-1897