

PMX-SERIES

STEREO POWER MIXER with DIGITAL EFFECT



PMX-SERIES

Stereo Power Mixer 6/8/12 Channel

TECHNICAL SPECIFICATION

POWER SECTION :	PMX-602	PMX-802	PMX-1202
Power Output	250W x 2 @ 4Ω	250W x 2 @ 4Ω	300W x 2 @ 4Ω
.....	150W x 2 @ 8Ω	150W x 2 @ 8Ω	180W x 2 @ 8Ω
T.H.D.	0.1% below	0.1% below	0.1% below
Power Requirement	AC 220V	AC 220V	AC 220V
Power Consumption	650W	650W	800W
MIXER SECTION :			
Input Channel Sensitivity			
MIC	-60dB		
Stereo Channel Input	-40dB		
EFX Send	-20dB		
EFX Return	-20dB		
Output	4V MAX		
Signal to Noise Ratio	-80dB		
Parametric EQ			
HI	+/-15dB, 10kHz		
MID	+/-15dB, 250kHz-6kHz		
LOW	+/-15dB, 60Hz		
		PMX-602 : 6 Mono Input + Digital Effect	
		PMX-802 : 8 Mono Input + Digital Effect	
		PMX-1202 : 12 Mono Input + Digital Effect	

<http://www.nts-solution.com>

All features & specifications are subjected to change without notice.



บริษัท เอ็นทีเอส อิเล็กทรอนิกส์ โซลูชั่น จำกัด
NTS Electronic Solution Co., Ltd.

1439-1441 ถนนเจริญนคร แขวงบางลำภูล่าง เขตคลองสาน กรุงเทพฯ 10600

โทรศัพท์: 0-2438-7023-4, 0-2437-7639 โทรสาร: 0-2437-1897

<http://www.nts-solution.com> E-mail: nts@nts-solution.com

1439-1441 Charoennakorn Rd. Banglumpoolang Klongsan Bangkok 10600, Thailand

Tel: (+66-2) 438-7023-4, (+66-2) 437-7639 Fax: (+66-2) 437-1897