

# SMR-SERIES

STEREO MIXER with 16 DSP EFFECT & USB INPUT

# NTS



SMR6 : 6 Channel Mixer (2 Mono / 2 Stereo)

SMR8 : 8 Channel Mixer (4 Mono / 2 Stereo)

## TECHNICAL SPECIFICATION

- Mono and stereo input with gold plated XLR and balanced line input
- 3 band EQ on mono input and 2 band EQ on stereo input
- Peak LED on all mono and stereo channel
- 1 Aux send per channel for external effects and monitoring
- Highly accurate 8 segment bargraph meter
- 16 DSP digital multi effect
- +48V phantom power supply
- MP3 input and playback

### Input Channel

Mic Input ..... Electronically balanced  
: Frequency Response ..... 10Hz to 200KHz  
: Gain Range ..... +14dB to +60dB  
: SNR ..... 120dB E.I.N.  
Line Input ..... Electronically balanced  
: Frequency Response ..... 10Hz to 130KHz  
: Gain Range ..... -6dB to +38dB  
: SNR ..... 95dB E.I.N.

### Stereo Channel

Frequency Response ..... 10Hz to 70KHz  
Gain Range : Line ..... -8dB to +15dB  
: Mic ..... +13dB to +60dB  
SNR : Line ..... 96dB  
: Mic ..... 104dB E.I.N.

### Equalization

Low ..... 80Hz, +/-15dB  
Mid ..... 2.5KHz, +/-15dB  
High ..... 12KHz, +/-15dB

### Main Mix

Main Output ..... +28dBu balanced / +22dBu unbalanced  
AUX Send ..... +22dBu unbalanced  
Tape Out ..... +22dBu unbalanced  
Phone Output ..... +15dBu

### Physical Dimension and Weight

Dimension [HxWxD] ..... 72 x 210 x 250 mm. [SMR6]  
..... 72 x 260 x 250 mm. [SMR8]  
Weight ..... 3.0 kg. [SMR6]  
..... 3.7 kg. [SMR8]

# NTS

บริษัท เอ็นทีเอส อิเล็กทรอนิกส์ โซลูชั่น จำกัด  
NTS Electronic Solution Co., Ltd.

1439-1441 ถนนเจริญนคร แขวงบางลำภูล่าง เขตคลองสาน กรุงเทพฯ 10600

โทรศัพท์: 0-2438-7023-4, 0-2437-7639 โทรสาร: 0-2437-1897

<http://www.nts-solution.com> E-mail: [nts@nts-solution.com](mailto:nts@nts-solution.com)

1439-1441 Charoennakorn Rd. Banglumpoolang Klongsan Bangkok 10600, Thailand

Tel: (+66-2) 438-7023-4, (+66-2) 437-7639 Fax: (+66-2) 437-1897

<http://www.nts-solution.com>

All features & specifications are subjected to change without notice.