GS-SERIES

STEREO MIXER WITH 16 DSP EFFECT

GS-8FX : 8 Channel Mixer (4 Mono / 2 Stereo) with 16 DSP Effect

GS-12FX : 12 Channel Mixer (8 Mono / 2 Stereo) with 16 DSP Effect

TECHNICAL SPECIFICATION

- 3 band EQ on all input
- 1 Aux send for external effects and monitoring
- Peak LED on all input
- LOW CUT switch on mono input
- MUTE and SOLO switch on all input
- Built in 16 program digital effect
- Stereo output and 2 ALT output
- +48V phantom power supply

MAIN SPECIFICATION :

Channel Mic/Line ..... 8 CH : 4 Mono/2 Stereo [GS-8FX]
..... 12 CH : 8 Mono/2 Stereo [GS-12FX]

Total Harmoinc Distortion ..... ≤ 0.05%
Frequency Response ..... 5Hz-50kHz, +/-3dB
S/N Ratio ..... ≥ -103dB
Max Output ..... 4V Max
Input Sensitivity : Mic ..... -60dB
: Line ..... -40dB
: Effect Return ..... -40dB
: Aux in ..... -40dB
: Tape in ..... -40dB
Mono Channel EQ : High ..... +/-15dB, 12KHz
: Mid ..... +/-15dB, 2.5KHz
: Low ..... +/-15dB, 80Hz
Stereo Channel EQ : High ..... +/-15dB, 12KHz
: Mid ..... +/-15dB, 2.5KHz
: Low ..... +/-15dB, 80Hz
Power Requirement ..... AC 220V/50Hz

http://www.nts-solution.com

All features & specifications are subjected to change without notice.

บริษัท เอ็นทีเอส อิเล็กทรอนิกส์ โซลูชั่น จำกัด
NTS Electronic Solution Co., Ltd.

1439-1441 ถนนเจริญนคร แขวงบางลำภูล่าง เขตคลองสาน กรุงเทพฯ 10600
โทรศัพท์: 0-2438-7023-4, 0-2437-7639 โทรสาร: 0-2437-1897
http://www.nts-solution.com E-mail: nts@nts-solution.com
1439-1441 Charoennakorn Rd. Banglumpoolang Klongsan Bangkok 10600, Thailand
Tel: (+66-2) 438-7023-4, (+66-2) 437-7639 Fax: (+66-2) 437-1897