

### TECHNICAL SPECIFICATION



+ Line Transformer + Power Amplifier

#### ■ NC-402 / 402T

Rated power .....	25W RMS
Power [MAX] .....	50W
Bass speaker .....	4"
Speakers .....	1 tweeter
Connections .....	2-pole terminal
Sensitivity .....	88dB
Impedance .....	8Ω
Frequency-range .....	70Hz ~ 18KHz
Dimension [HxWxD] .....	243x151x150 mm.
<b>NC-402T</b> Line Transformer .....	2/4/8/16 W (100V)

#### ■ NC-502 / 502T / 502A

Rated power .....	35W RMS
Power [MAX] .....	75W
Bass speaker .....	5"
Speakers .....	1 tweeter
Connections .....	2-pole terminal
Sensitivity .....	89dB
Impedance .....	8Ω
Frequency-range .....	60Hz ~ 18KHz
Dimension [HxWxD] .....	247x158x152 mm.
<b>NC-502T</b> Line Transformer .....	2/4/8/16 W (100V)
<b>NC-502A</b> Power output .....	25W RMS
Frequency-range .....	20Hz ~ 20KHz
Equalization .....	2 band EQ +/-15dB
Gain .....	30dB (max)

#### ■ NC-602 / 602T

Rated power .....	50W RMS
Power [MAX] .....	100W
Bass speaker .....	6.5"
Speakers .....	1 tweeter
Connections .....	2-pole terminal
Sensitivity .....	89dB
Impedance .....	8Ω
Frequency-range .....	55Hz ~ 20KHz
Dimension [HxWxD] .....	348x208x203 mm.
<b>NC-602T</b> Line Transformer .....	4/8/16/30 W (100V)

#### ■ NC-802 / 802T

Rated power .....	85W RMS
Power [MAX] .....	125W
Bass speaker .....	8"
Speakers .....	1 tweeter
Connections .....	2-pole terminal
Sensitivity .....	90dB
Impedance .....	8Ω
Frequency-range .....	45Hz ~ 20KHz
Dimension [HxWxD] .....	420x255x250 mm.
<b>NC-802T</b> Line Transformer .....	4/8/16/30 W (100V)

<http://www.nts-solution.com>

All features & specifications are subjected to change without notice.



บริษัท เอ็นทีเอส อิเล็กทรอนิกส์ โซลูชั่น จำกัด  
NTS Electronic Solution Co., Ltd.

1439-1441 ถนนเจริญนคร แขวงบางลำภูล่าง เขตคลองสาน กรุงเทพฯ 10600

โทรศัพท์: 0-2438-7023-4, 0-2437-7639 โทรสาร: 0-2437-1897

<http://www.nts-solution.com> E-mail: [nts@nts-solution.com](mailto:nts@nts-solution.com)

1439-1441 Charoenakorn Rd. Banglumpoolang Klongsan Bangkok 10600, Thailand

Tel: (+66-2) 438-7023-4, (+66-2) 437-7639 Fax: (+66-2) 437-1897