

# PKA-SERIES

POWER MIXER with EFFECT / USB / BLUETOOTH



## PKA-SERIES

Stereo Power Mixer with Digital Effect / USB Input / BLUETOOTH Function

### TECHNICAL SPECIFICATION

- 3 band EQ on all input
- 1 Aux send for external effects and monitoring
- Peak LED on all input
- PHANTOM, PAD and MUTE switch on all input
- Built in 99 program digital effect
- USB interface for MP3 input and playback with digital display
- BLUETOOTH function
- 7 band graphic EQ
- +48V phantom power supply

- PKA-8 : Power Mixer 8 Mono Input
- PKA-12 : Power Mixer 12 Mono Input
- PKA-16 : Power Mixer 16 Mono Input

#### SPECIFICATION :

Power Output .....	300W x 2 @ 8Ω
.....	500W x 2 @ 4Ω
Frequency Response .....	20Hz - 20KHz
T.H.D. ....	0.005% / 0.004% A-weighted
Signal to Noise Ratio .....	110dB / 112dB A-weighted
EQ : HIGH .....	+/-15dB, 12kHz
: MID .....	+/-15dB, 3kHz
: LOW .....	+/-15dB, 80Hz

<http://www.nts-solution.com>

All features & specifications are subjected to change without notice.

**NTS** บริษัท เอ็นทีเอส อิเล็กทรอนิกส์ โซลูชั่น จำกัด  
NTS Electronic Solution Co., Ltd.

1439-1441 ถนนเจริญนคร แขวงบางลำภูล่าง เขตคลองสาน กรุงเทพฯ 10600

โทรศัพท์: 0-2438-7023-4, 0-2437-7639 โทรสาร: 0-2437-1897

<http://www.nts-solution.com> E-mail: [nts@nts-solution.com](mailto:nts@nts-solution.com)

1439-1441 Charoennakorn Rd. Banglumpoolang Klongsan Bangkok 10600, Thailand

Tel: (+66-2) 438-7023-4, (+66-2) 437-7639 Fax: (+66-2) 437-1897